

PB L20 BRUSHLESS

ADVANTAGES

- 18V Cordless drill / screwdriver / hammer drill with a maximum 50Nm tightening torque and a powerful BRUSHLESS motor, without carbon brushes .
- ø13mm keyless chuck with safety lock.
- 21 clutch settings plus 3 adjustment settings to control the tightening torque. The torque is limited by the clutch to release the gears if the drilling bit gets stuck, protecting the tool and the user.
- 2 mechanical speeds for a better tightening torque.

Speed / Setting 1: maximum torque up to 500 rpm for screwdriving, metal drilling and hardwood drilling with large-diameter drill bits.

Speed / Setting 2: minimum torque and maximum speed up to 2000 rpm for drilling materials and soft woods, with small diameter drill bits, and for hammer drilling construction materials.

- Reversible & electronic with microprocessor.
- Powerfull brushless motor to increase the tool's efficiency, decreasing heating while increasing the tool and batteries lifespan and performance.
- More power

- Liahter
- More battery use time
- Less breakdowns

DATA SHEE

- Greater autonomy
- STAYER Li-ion HIGH-TECH Battery, from the L20 Series with overload protection, battery discharge, overheating, protection against short circuits. LED battery level charge.
- Comfortable belt clip to hang the tool while it's not being used
- LED worklight for dark environments and maximum safety.



18 V Battery voltage - Lithium Battery capacity 2.0/4.0/5.0 Ah No load speed 0-500 / 0-2000 min-1 *Impacts* 0-7500 / 0-30000 ipm Battery charge time 60 / 90 min Chuck capacity Ø 2-13 mm Insertion 1/2"x20 UNF Max. wood drilling capacity Ø 45 mm Max. steel drilling capacity Ø 13 mm Max. masonry drilling capacity Ø 13 mm 60 Nm Tiahtenina toraue Torque settings 21 + 3 Positions Weight 1.2 Kg

INCLUDES

	5 >	5];	PE-HD	IKF
PB L20 BRUSHLESS	X	Х	Х	х
PBL 2032 PK BRUSHLESS	2x 2.0Ah	~	~	Х
PBL 2032 PIKF BRUSHLESS	3x 2.0Ah	~	Х	~
PBL 2033 PK BRUSHLESS	1x 2.0 + 4.0Ah	~	~	Х
PBL 2034 PK BRUSHLESS	2x 4.0Ah	~	Х	~
PBL 2035 PK BRUSHLESS	2x 5.0Ah	~	Х	~

